

Statement in support of application for merger authorisation

Annexure 'TH-11'

PROPOSED ACQUISITION BY BROOKFIELD LP AND MIDOCEAN ENERGY OF ORIGIN ENERGY LIMITED

Statement of: **Thomas Andrew Hallam**

Address: 31/2 Southbank Boulevard, Southbank VIC 3006

Occupation: General Manager, Regulation & Network Strategy, AusNet Services Limited

Date: 26 May 2023

Part 3—Records and reporting

27 Records

- (1) An accepted ESMS operator must, in accordance with this regulation, establish and maintain a system for keeping records relating to its accepted ESMS.

Penalty: 20 penalty units.

- (2) The accepted ESMS operator must keep the following records—
- (a) the accepted ESMS;
 - (b) any revisions of the accepted ESMS;
 - (c) any written audit reports of the accepted ESMS;
 - (d) any reports of investigations of incidents involving—
 - (i) if the accepted ESMS operator is an employer operator, the carrying out of electrical work; or
 - (ii) if the accepted ESMS operator is an MEC, the MEC's supply network; or
 - (iii) if the accepted ESMS operator is an asset operator, the operator's complex electrical installation;
 - (e) a copy of each report given by the accepted ESMS operator to Energy Safe Victoria;
 - (f) if the accepted ESMS operator is an employer operator or asset operator, a register of the names and qualifications of persons nominated to carry out electrical work under the accepted ESMS.

- (3) The accepted ESMS operator must keep records under subregulation (2)—
- (a) at the address nominated by the accepted ESMS operator in the accepted ESMS; and
 - (b) in a manner that makes their retrieval reasonably practicable; and
 - (c) in a secure manner; and
 - (d) for the period of 7 years after their creation.

28 Requirements for reporting of serious electrical incidents by major electricity companies

- (1) For the purposes of section 142(1) and (2) of the Act, an electricity supplier that is an MEC must, if this regulation applies—
- (a) notify Energy Safe Victoria of a serious electrical incident as soon as practicable as specified in reporting guidelines published by Energy Safe Victoria as issued or amended from time to time; and
 - (b) provide Energy Safe Victoria with a report of the incident in accordance with the reporting guidelines.
- (2) This regulation applies if a serious electrical incident—
- (a) caused the death of or injury to a person; or
 - (b) caused significant property damage; or
 - (c) caused significant disruption to the community; or
 - (d) involved an electric line with a nominal voltage of more than 66 000 volts; or
 - (e) involved an imminent risk of electrocution; or